

## Futronic FS80 USB2.0 Fingerprint Scanner

### Major features and benefit:

Futronic's FS80 USB2.0 Fingerprint Scanner uses advanced CMOS sensor technology and precise optical system to deliver high quality fingerprint image. It can capture an raw fingerprint image into PC in 100ms. So it is good for any fingerprint recognition application.

Its finger scanning window is a crown glass with a thickness of 14mm. So it is much more reliable and robust compared to any semiconductor type fingerprint sensor.

The finger is illuminated by 4 infra-red LEDs during scanning and the light intensity is automatically adjusted according to scanning fingerprint's characteristics (wet, dry, blurred, etc) to optimized the quality of the captured fingerprint image.

Special electronic circuit is built into FS80 to do Live Finger Detection(LFD). That is, with appropriate software in PC, user can select this LFD feature so that only live finger's fingerprint will be scanned into PC. Fake fingers made from silicone rubber, play-doh, etc. will be rejected. This LFD feature is included in all Futronic's standard software.



### Electrical characteristics

- Light source: Infrared LED
- Supply voltage: DC 4.5-5.5V via USB port
- Power consumption:
- Active <550mW(during finger scanning),
- Standby <200mW,
- sleep mode <15mW
- ESD contact – 8KV no permanent damage
- ESD air discharge - 16KV no permanent damage.

### Hense Technology Pte Ltd

Blk 212, Hougang Street 21, #03-319  
Singapore 530212  
Tel: +65-62859890 Fax: +65-62859890  
Email: sales@hensetech.com.sg  
Website: [www.hensetech.com.sg](http://www.hensetech.com.sg)

### Specifications

- Finger scanning window size is 16 x 24mm
- Image resolution is 480x320 pixel, 500 DPI
- Raw fingerprint image file size is 150K byte
- With Live Finger Detection (LFD) feature
- USB 2.0 compatible, plug and play device
- With a 2M standard USB cable
- Small size, 45 x 63 x 26 mm
- Light weight, 120 gram
- Operation temperature: -10 to +55 C

### USB drivers and Application Programming Interface (API) for FS80 to capture fingerprint image on the following platforms:

- Windows 2000/XP
- Vista/2008 32 bit and 64 bit
- Windows 7, 32 bit and 64 bit
- Windows SDK supports CE 5.0 and 6.0 (for both x86 and ARM9)
- Linux SDK with kernel 2.4 or after (for both x86 and ARM9)

### Compliant to following standards

- Microsoft WHQL
- FCC and CE
- RoHS